

DVR QUICK INSTALLATION GUIDE

HS-DVR

THANK YOU FOR CHOOSING ANTAIVISION !











I:STEPS FOR CLOUD ACCESS FROM MOBILE DEVICE



1, Step One:Startup Wizard

They system will automatically open the 'Setup Wizard' screen.to guide the User to set up basic settings.You click ' next' to continue.

User Name admin Password Lack Authority	
OK Cancel	2

2.Step Two: After Step One.the system will display the 'login' Screen, as shown in Picture 2, othe r functions can be carried out after user login. The text edit box' User name' and 'Password' don' t need to enter anything,

The system 'user name' default is : admin and the 'Password' only left it blank and click 'OK' to complete login.

Time - Lang	uage Configuration	
Time Zone	[UTC+08:00]Beijing,Urumqi,Tε	
System Time	2017 - 07 - 13 08: 58: 49	
Date Format		
Date Separator		
Time Format	24-HOUR 💌	
DST		
Enable	0	
 Day of Weel 	Date	
Start:	2017-05-01 01:01	
End:	2017 - 10 - 01 01:01	
Modify Languag	e	
Language	ENGLISH •	
	Previous Next Cancel	3

3,Step three : After the step two,it shows the picture 3:Set up language,date ,and Time zone,click 'next' when finished.



4,Step Four: After the step three , it as shown in the picture 4,you only to do is click 'next' .



5,**Step Five** :After the step four, it as shown in the picture 5:Scan the QR code to begin downloading he app directly, It can be download by the phone which is Iphone or Android system.

By the way:another method to download the app,you can open your app store or Google Play by your phone to search 'XMEye' and download the app Click 'next ' when finished.







When you finished register account, you go back to the 'XMEye' app homepage and enter your user name and password and click 'Cloud Login' button to complete login. (2)If you don't want to register an account ,you can click 'Login' to complete login directly.





7.**Step Seven** : After the step six, you complete login the app ,it shows as picture 11 : Click "+" to add device.

8.After you click "+", it show as picture 12:



You only to do is set device name by yourself and left the pasword and port blank: don't change the user name, it is default :admin.

And then click the Serial Number's QR code to scan the QR code as the picture 6

Shown, then 'SN QR code' or you can enter a serial number, pls click the right button of the mouse, it shows the 'Main Menu' and click it ,pls see the picture below:



Then click 'info' and continue



Then you can see the serial No and enter it into your app.

When you finish entering your Device name and serial number, click 'ok' to finish.



Then you can view by your

phone now:





. . .

Q

HD

SD

Talking

Transfer resolution



Refresh



Play back

II:STEPS FOR CLOUD ACCESS FROM INTERNET EXPLORER

1,Enter the link :www.xmeye.net into your internet explorer ,it shows as below: You can set language from Chinese to English.

TTTY-y=	-20	1000		中文(中文-簡体) English 中文(中文- 留題) 意大利語(taliano) 西班牙書(Español) 情語(Pycconi) 法語(Françai)	FElweb290 APP FE
	五大优势		按用户	總加(Deutsch) 葡萄牙語(Português) 巴西(Português - BR) 尊语(한국의) 建克(České)	-
	3.0云服务全新升级		1 用户名		100
	连递率更高		🔒 電码		1.000
	速度更快		验证药	18550	
	安全有保障		口记住密码	找回收到	1.00
	稳定更性强		ŝ	禄	and the second second
		••	第一次整要,请你击新手	N Ð	
			注	im 🦽	4

2, Click 'by Device' and enter your device serial NO.and set the user name as 'admin', pls note :you need set the user name as 'admin', so you can login successfully. You don' t meed to input password, left it blank and input the Verify ,and click 'login and preview' to continue.

/myeye	English(English) • Install ActiveX APP Download	
and the second second		
Announcement	By User By Device	
1. The firmware released after Sep 28th, 2012, the serial No. had been updated from 12-bit to 16-bit.	SerialNO.	
2. Cloud FAQ.	Password	
3. The instructional videos of using cloud service.	Verify Verify	
4. Announcement of system account integration	Login and Preview Please Click "Enter Guide" if you visit first	
	Register	

III:FUNCTION

🗟 System > Ne	twork
Net Card	Wire Netcar(UDHCP Enable
IP Address	192 . 168 . 1 . 99
Subnet Mask	255 . 255 . 255 . 0
Gateway	192 . 168 . 1 . 1
Primary DNS	192 . 168 . 1 . 1
Secondary DNS	
Media Port	34567
HTTP Port	80
HS Download	
Transfer Policy	Quality Prefe -
	OK Cancel (2

1, Main Menu/System/Network

System > DISPLAY	X
Channel Title Set	
Time Display 🗹 Channel Title 🗹	
Record Status 🗹 Alarm Status 🔽	
Deflick 2 Transparancy 175	
Channel 1	
Region Cover	
Time Display 🔽 Channel Title 🗹 🦲 Set	₩
	OK Cancel 23

2,Main Menu/System/Display



3, Main menu/advanced/storage



4.main menu/info/HDD info



5,Main menu/record/record conf





27)

😤 Alarm > Moti	on Detect
Channel Sensitivity	Image: Image
Period AlarmOut Record Channel Tour Snapshot PTZ Activation Show Message Buzzer FTP upload	Set MD Interval 2 Sec. 1 OutDelay 10 Sec. 1234 * 1234 * 1234 * 1234 * Set PostRec 10 Sec. Send Email * Vite Log *
	Advanced OK Cancel

7,main menu/alarm/motion detect



28



Any question, please contact ATcloud Custome Support:

1.Contact person:Icey

- 2.Whats app:8613537732900
- 3.Email add:info@antaivision.com