

QT548-841-5

8-QSM6006B Cameras



1- QT548 DVR w/ 500GB HD

Product Overview

- Q-See does it again with its new 8 Channel DVR with 8 high-resolution cameras.
 - This Costco-exclusive system has everything you need to watch over your loved ones and protect your property. The 8 weatherproof bullet cameras give you flexibility for placement almost anywhere. Connect the DVR to a 19" or larger HDMI or VGA ready monitor or a television to view all the video feeds simultaneously, individually or a few at a time.
 - The pre-installed AV Rated SATA 500GB hard drive can retain hours or days of video. The DVR will support a drive up to 2 terabytes to expand your storage, and depending on your preferences, the system can be set to record only when motion is detected, eliminating the need to sift through hours of footage to find a specific event. You can also easily save any important video to a removable USB drive for storage or playback on a computer.
 - In addition to being able to control and monitor your system on-site, the QT548 DVR can be accessed remotely, whether over the Internet or on any of the supported mobile devices including the iPhone, iPad, Android, Windows phone 7 and BlackBerry devices. You can also receive e-mail alerts notifying you of detected events. Log into your system via Q-See mobile apps on your WiFi, 3 or 4G network or computer to check in on your family or employees.
You can also save critical events onto your computer for added security.
 - Our online knowledge base is ready to help you 24/7 and our tech support staff is available to help you online or over the phone Monday through Friday 8:30am to 5pm Pacific Coast time.
-

Main Features

- 8 Channel H.264 D1/CIF DVR
 - 8 cameras with 600TVL resolution
 - Weatherproof cameras for indoor or outdoor use
 - 120 feet of night vision
 - Remote internet monitoring (up to 10 users at the same time)
 - Mobile Phone Surveillance
 - Compatible with MAC and PC
 - Free Q-See Apps for iPhone, iPad, and Android remote viewing!
 - Free Apps for Blackberry , Windows Mobile and Windows Phone 7 viewing!
 - Receive instant email alerts and snapshot images when motion is detected
 - Zoom in on live or playback footage with 2X digital zoom!
-

Product Set-up

- Designed for Do It Yourself setup.
 - Comes with everything needed to setup except router for remote access.
 - Connect cameras to power supply with splitter and DVR, connect DVR to power supply, connect both power supplies to surge protector and power outlet.
 - Uses UPnP for easier IP address and port forwarding setup
-

Product ease of use

- Easy DIY setup of cameras and DVR
 - Easy to use menu interface
 - Mouse and remote included for easy menu navigation
 - UPnP enabled for easier IP address and port forwarding setup
-

Where product should be used

- Product can be used anywhere security is needed, homes, offices, factories, banks, retail stores, parks, playgrounds, etc.

Product spec-DVR1.

Compression – H.264

Operating System - Linux

Video Inputs – 8 BNC

Video Outputs – 2 BNC, 1 VGA, 1 HDMI

Audio Inputs/Outputs – 4/1

VGA Resolution - 800x600, 1024x768, 1280x1020, HDMI

Playback Resolution – CIF 352x240, D1 702x480

CIF Playback Frame Rate – 30

D1 Playback Frame Rate – 30

Record Bit Rate – 128kbps– 2Mbps

Storage - 1 SATA AV Rated Hard Drive up to 2TB (comes with 500GB HD)

OS support – WinXP, Vista, Win7, Mac OS 10.6/10.7

Browser Support – Internet Explorer, Google Chrome, Firefox, Safari

Smart Phone - iPhone/iPad, Android, Windows 7, Blackberry

Simultaneous Remote User's - 10

Product spec-DVR2.

Power Supply - 110-220 Volt input, 12 Volt 3A output

Power Consumption – 20 Watt

Alarm – 8 Inputs, 1 Output

Alarm Mode – Motion Detection, Sensor

USB ports – 2 USB 2.0, 1 for mouse, 1 for USB backup (Flash, Hard Drive)

Network Interface – RJ45, 10/100 mbsp

PTZ Interface - RS485, supports 128 presets, 8 cruises,

Multiplex – view live or playback video, record, backup, and view and backup video over the network or Internet at the same time

Product spec-QM6006B Camera

Weather proof Indoor/Outdoor IP66 rating.

Mounting Bracket - 3 axis

Resolution – 600TVL

Sensor – 1/3 in CMOS color with IR cut filter

Lens: 5mm (50° to 55° Field of View)

Night Vision - 42 LEDs up to 120 feet

AGC/BLC - Auto

S/N Ratio - >48dB

Power Consumption - <6 Watts (LEDs on)

Power Supply – 12v/600mA

Operating Temperature - 14 to 122°F 95% Humidity

Cable – 60feet Video/Power

FAQ

Question: I am not getting any audio from my cameras, Why?

Answer: The cameras that come with the package do not have built in microphones. If you want to hear audio from the camera you would need to run a powered microphone from the camera location and connect it to an audio in port on the back of the DVR. You will also need to connect an amplified speak to the audio out port on the DVR to hear the audio on the DVR.

Question: I can see the video on my screen but the mouse, remote, and buttons on the front of the DVR do not work, how can I access the menu?

Answer: Hold down the stop/escape button on the front of the DVR for around 10 seconds until you hear a beep and see if this gets the mouse, remote and buttons to work.

Question: The video on my QM6006B camera is very dark, how can I correct this?

Answer: Put your hand over the front of the camera for around 10 seconds, then remove your hand, you should hear a click and the filter on the camera should reset.